

[HOME](#) | [PRODUCTS](#) | [SOLUTIONS](#) | [SUPPORT](#) | [RESOURCE CENTER](#) | [PARTNERS](#) | [MICROSEMI](#)

home > Support

netware 3.12 cd install

- Install EZ-SCSI(aspixdos.sys, aspicd.sys, mscdex.exe)
- Change to CD-ROM drive letter
- cd\netware.312\english
- Type "install"
- Select "INSTALL NEW NETWARE V3.12"
- Insert "SYSTEM_1" disk
- Down server
- Rename "config.sys"
- Reboot
- Boot "server"
- Load AHA or AIC dsk driver
- Load "install"
- Mount "SYS volume"
- Load "aspicd.dsk"
- Load "cdrom.nlm"
- Type "cd device list"
- Type "cd mount 1(device number) netware_312"
- Select "COPY SYSTEM and PUBLIC FILES"
- Select F6(for CD-ROM)
- Type "netware_312:\netware.312\english"
- Completed installation

CD-ROM Mounted as a Volume

optional (:scan for new devices)

- Load "aspicd.dsk"
- Load "cdrom.nlm"
- Type "cd device list"
- Type "cd mount 1 (device number) (volume name)"

NOTE:

- If you have Novell 3.12 on diskette, you will find the drivers on the SYSTEM-2 diskette.
- Make sure you renamed config.sys to config.dos
- if you have an AHA-1510 try load aha1510 port=xxx sync=off parity=off
- latest version of aspicd.dsk will be available on www.adaptec.com

Support Resources

- [Support Updates on Twitter](#)
- [TSID Importance](#)
- [Register My Product](#)
- [Support Options](#)
- [Contact Support](#)
- [RMA Information](#)
- [Compatibility Report](#)

Products

Products Overview
Product selector
Cables & Accessories
End of Life Products
Outlet Store
All Products

Solutions

Solutions Overview
Data Center Solutions
maxCache Solutions
ZMCP Solutions
Hybrid RAID Solutions
Green IT Solutions
maxView Storage Manager

Support

Downloads
Knowledgebase
Register Your Product
Compatibility Reports
TSID Importance
Support Options
RMA Information
Contact Support

Resources

Resources
Datasheets
Whitepapers & Briefs
Case Studies
Videos & Webinars
Compatibility Reports
Storage Advisors Blog
Facebook
Twitter

Partners

Channel Partners
Ecosystem Partners
Industry Alliances
Contact Us